

Part number	LVDS-FI-X30HL-DP2.0-2x15P-400-RTD2483	
Type	LVDS cable	
Description	LVDS cable between P215 and RTD2483, CON1= X30HL CON2= DP2.0-2x15P length = 400 mm	
Length	400	
Connector 1	FI-X30HL	
Connector 2	DP2.0-2x15P	

Connector 1	
FI-X30HL	
1	RXO0-
2	RXO0+
3	RXO1-
4	RXO1+
5	RXO2-
6	RXO2+
7	GND
8	RXOC-
9	RXOC+
10	RXO3-
11	RXO3+
12	RXE0-
13	RXE0+
14	GND
15	RXE1-
16	RXE1+
17	GND
18	RXE2-
19	RXE2+
20	RXEC-
21	RXEC+
22	RXE3-
23	RXE3+
24	GND
25	
26	
27	
28	Vcc
29	Vcc
30	Vcc

top view Connector 2			
DP2.0-2x15P			
1	Vcc	Vcc	2
3	Vcc	GND	4
5	GND		6
7	RXO0-	RXO0+	8
9	RXO1-	RXO1+	10
11	RXO2-	RXO2+	12
13	GND	GND	14
15	RXOC-	RXOC+	16
17	RXO3-	RXO3+	18
19	RXE0-	RXE0+	20
21	RXE1-	RXE1+	22
23	RXE2-	RXE2+	24
25	GND	GND	26
27	RXEC-	RXEC+	28
29	RXE3-	RXE3+	30

NO. (管脚)	SYMBOL (板上丝印)	DESCRIPTION (描述)
1	VCC	Power for panel (驱屏电源)
2	VCC	Power for panel (驱屏电源)
3	VCC	Power for panel (驱屏电源)
4	GND	Ground (地)
5	GND	Ground (地)
6	NC	NC
7	O0-	LVDS ODD 0- Signal (LVDS 奇数 0-信号)
8	O0+	LVDS ODD 0+ Signal (LVDS 奇数 0+信号)
9	O1-	LVDS ODD 1- Signal (LVDS 奇数 1-信号)
10	O1+	LVDS ODD 1+ Signal (LVDS 奇数 1+信号)
11	O2-	LVDS ODD 2- Signal (LVDS 奇数 2-信号)
12	O2+	LVDS ODD 2+ Signal (LVDS 奇数 2+信号)
13	GND	Ground (地)
14	GND	
15	OC-	LVDS ODD Clock- Signal (LVDS 奇数时钟-信号)
16	OC+	LVDS ODD Clock+ Signal (LVDS 奇数时钟+信号)
17	O3-	LVDS ODD 3- Signal (LVDS 奇数 3-信号)
18	O3+	LVDS ODD 3+ Signal (LVDS 奇数 3+信号)
19	E0-	LVDS EVEN 0- Signal (LVDS 偶数 0-信号)
20	E0+	LVDS EVEN 0+ Signal (LVDS 偶数 0+信号)
21	E1-	LVDS EVEN 1- Signal (LVDS 偶数 1-信号)
22	E1+	LVDS EVEN 1+ Signal (LVDS 偶数 1+信号)
23	E2-	LVDS EVEN 2- Signal (LVDS 偶数 2-信号)
24	E2+	LVDS EVEN 2+ Signal (LVDS 偶数 2+信号)
25	GND	Ground (地)
26	GND	
27	EC-	LVDS EVEN Clock- Signal (LVDS 偶数时钟-信号)
28	EC+	LVDS EVEN Clock+ Signal (LVDS 偶数时钟+信号)
29	E3-	LVDS EVEN 3- Signal (LVDS 偶数 3-信号)
30	E3+	LVDS EVEN 3+ Signal (LVDS 偶数 3+信号)